

**Accessory Switches**
**Momentary Windlass Switch**  
**Two Positions: On-Off (normally Off)**  
**On with button depressed, spring return to Off**

- Brass case, stem, terminals and mounting hardware.
- Moisture repellent insulators.
- For 6-36 volt, D.C. electrical systems.
- Normally mounted vertically, typical mounting plate and rubber cover shown in phantom (not supplied).


**No. 9250**

- Anodized aluminum plunger button  $1\frac{5}{16}$ " (23.81mm) diameter.
- Plunger button loose, must be held in place with rubber cover.
- Silver contacts.
- Molded plastic insulator with protective barrier between terminals.
- Two screw terminals.
- Mounting stem  $\frac{5}{8}$ "-32 thread,  $\frac{7}{16}$ " (11.11mm) long.
- Fits mounting plate up through  $\frac{3}{16}$ " (4.76mm) thick.

**Blower & Ignition Switch**  
**Four Positions:**  
**Off - Blower - Ignition & Blower - Ignition**
**No. M-601**

- Plasticized brass case seals out moisture and dirt.
- Two 12 gauge and two 18 gauge insulated copper wire leads, 18" (457.20mm) long.
- Chrome plated die cast lever.
- Polished aluminum face plate with maroon enamel finish.
- Brass mounting stem  $\frac{1}{2}$ " (12.70mm) dia., 1  $\frac{1}{2}$ " (38.10mm) long.
- Fits panels up through 1  $\frac{1}{8}$ " (28.57mm) thick.
- Wiring instructions included.


**Electronic Dimmer Switch**  
**For variable intensity control of lighting:**  
**Bright to Dim**
**No. 74600-02**

- For 12 volt, D.C. negative ground systems, 14.7 volt D.C. maximum.
- Sealed case and "O" ring on shaft.
- Cool operating due to low heat generation.
- Intensity settings are not load sensitive.
- 4 amp capacity.
- Mounting stem  $\frac{7}{16}$ "-28 thread, .45" (11.43mm) long.
- Die cast case 1  $\frac{9}{16}$ " (39.69mm) dia., .883" (22.42mm) long.
- Three wire (load, battery, ground) Packard connector.
- Fits panels up through  $2\frac{9}{32}$ " (23.01mm) thick.


**Bilge Pump Switch**  
**Three positions: Automatic - Off - Manual**
**No. M-552**


- Brass case.
- Chrome plated die cast lever.
- Polished aluminum face plate with maroon enamel finish.
- 3 brass screw terminals.
- Brass mounting stem  $\frac{7}{16}$ " (11.11mm) dia., 1  $\frac{1}{16}$ " (26.98mm) long.
- Fits panels up through  $1\frac{3}{16}$ " (20.63mm) thick.
- Wiring instructions included.


**Universal Off-On Switch**

Rating at 14 volts, D.C. • 50 amps

**No. M-288**

- Extra heavy duty.
- Silver contacts.
- Steel case, plated to resist corrosion.
- Die cast lever.
- Two brass screw terminals.
- Mounting stem  $\frac{5}{8}$ " (15.87mm) dia.,  $\frac{3}{4}$ " (19.05mm) long.
- Fits panels up through  $1\frac{7}{32}$ " (13.05mm) thick.


**Horn Button Switch**
**No. 96101**
**No. 96101-BP\***

- Steel case, plated to resist corrosion.
- Black plastic button,  $1\frac{3}{16}$ " (20.63mm) dia.
- 2 screw terminals.



\*Packaged in bubble pack. Please consult price list for standard bubble pack quantities.